

Finite frequency quantum noise in an interacting mesoscopic conductor

F.W.J. Hekking^{1,2} and J.P. Pekola²

¹*Laboratoire de Physique et Modélisation des Milieux Condensés,
CNRS & Université Joseph Fourier,
BP 166, 38042 Grenoble-cedex 9, France*

²*Low Temperature Laboratory, Helsinki University of Technology,
P.O. Box 3500, 02015 HUT, Finland*

Abstract

We present a quantum calculation based on scattering theory of the frequency dependent noise of current in an interacting chaotic cavity. We include interactions of the electron system via long range Coulomb forces between the conductor and a gate with capacitance C . We obtain explicit results exhibiting the two time scales of the problem, the cavity's dwell time τ_D and the RC -time τ_C of the cavity *vis à vis* the gate. The noise shows peculiarities at frequencies of the order and exceeding the inverse charge relaxation time $\tau^{-1} = \tau_D^{-1} + \tau_C^{-1}$.

PACS numbers: 72.70.+m, 73.23.-b, 05.45.Mt

Electrical noise in mesoscopic conductors is known to yield a wealth of information on microscopic mechanisms of transport [1]. Recently, focus in theory and experiment has shifted from studies of noise spectra to those of general current statistics including all the moments of current [2]. Meanwhile, though, important properties of the standard second moment, i.e., the part of statistics that is normally associated with noise, are still to be uncovered in several important aspects of direct relevance to experimental investigations. An example is finite frequency noise of a mesoscopic conductor. The interest of studying it is two-fold. First, one expects that the noise will probe the intrinsic dynamics of the conductor at the Thouless energy (inverse dwell time τ_D). Second, at finite frequency, current is no longer spatially homogeneous, and charge piles up in the conductor. Coulomb interaction screens this pile-up of charge, at a characteristic charge relaxation frequency which may well be different from $1/\tau_D$. Therefore, any theoretical treatment of finite-frequency noise should take interaction effects into account [1]. Calculation of the noise spectrum of an arbitrary, interacting mesoscopic conductor constitutes a formidable task, which has so far been accomplished in specific cases only, like mesoscopic capacitors [1], Coulomb blockade systems [3] and Luttinger liquids [4]. Finite frequency noise spectra are of experimental relevance, as they can be measured with recently developed quantum detectors [5]. These noise detectors distinguish finite positive and negative frequencies, i.e. they separately probe emission and absorption.

In this article we present a self-consistent theory of high frequency quantum noise of a chaotic cavity. We calculate emission and absorption spectra with the help of scattering theory, including interactions to ensure current conservation. Besides providing timely guidelines for experiments on noise spectroscopy, our theory paves the way towards a consistent calculation of the finite frequency higher moments of current, in particular the presently actively investigated third cumulant [6]. We obtain the noise spectrum of a chaotic quantum cavity capacitively connected to a screening gate, see Fig. 1. We believe these results to be representative, at least on a qualitative level, for an arbitrary interacting conductor. Specifically we show that, under realistic conditions, the noise spectrum is governed by the charge relaxation time τ , where $\tau^{-1} = \tau_D^{-1} + \tau_C^{-1}$, with the RC -time τ_C of the cavity. The dwell time is $\tau_D = hN_F/N$, and $\tau_C = hC/(Ne^2)$, where N_F is the density of states of the cavity at the Fermi level, $N = N_L + N_R$ is the sum of the number of channels of the left lead and right lead, respectively, and C is the geometric capacitance.

In the scattering theory of quantum transport the current operator is given by [7]

$$\hat{I}_\alpha(t) = \frac{e}{2\pi\hbar} \sum_n \int dE dE' e^{i(E-E')t/\hbar} \times \left[\hat{a}_{\alpha n}^\dagger(E) \hat{a}_{\alpha n}(E') - \hat{b}_{\alpha n}^\dagger(E) \hat{b}_{\alpha n}(E') \right]. \quad (1)$$

The operator $\hat{a}_{\alpha n}^\dagger(E)$ ($\hat{a}$) creates (annihilates) electrons incident upon the scatterer with energy E in the transverse channel n in lead α . Similarly, $\hat{b}^\dagger$, $\hat{b}$ denote electrons in the outgoing states. For the two-terminal set-up depicted in Fig. 1a, α takes values L and R for the left and right leads respectively. The operators $\hat{a}$ and $\hat{b}$ are related by the scattering matrix s , $\hat{b}_{\alpha n}(E) = s_{\alpha\gamma;nm}(E) \hat{a}_{\gamma m}(E)$ [8]. The matrix s is unitary and has dimensions $N \times N$. Using s , we eliminate the $\hat{b}$ operators from Eq. (1). Defining the current matrix

$$A_{\alpha\gamma;mn}^{(0)}(L, E, E') = \delta_{mn} \delta_{L\alpha} \delta_{L\gamma} - s_{L\alpha;mk}^\dagger(E) s_{L\gamma;kn}(E'), \quad (2)$$




FIG. 1: (a) Schematic presentation of the two-terminal scattering problem. (b) Scheme of a chaotic quantum cavity; the capacitor C accounts for the interactions.

we write current in the left lead as

$$\hat{I}_L(t) = \frac{e}{2\pi\hbar} \int dE dE' e^{i(E-E')t/\hbar} \times \hat{a}_{\alpha m}^\dagger(E) A_{\alpha\gamma;mn}^{(0)}(L, E, E') \hat{a}_{\gamma n}(E'). \quad (3)$$

The superscript (0) indicates that we deal with non-interacting electrons.

The average current-current correlation function in the left lead can now be written as $\langle \delta \hat{I}_L(t) \delta \hat{I}_L(0) \rangle = \int \frac{d\omega}{2\pi} e^{-i\omega t} S_{LL}(\omega)$, where we denote $\delta \hat{I}_L(t) \equiv \hat{I}_L(t) - \langle \hat{I}_L(t) \rangle$. Using Eqs. (2) and (3), and performing standard thermal averaging of products of operators $\hat{a}$ and $\hat{a}^\dagger$ for equilibrium reservoirs, we obtain the noise spectrum in the absence of interactions [1]

$$S_{LL}^{(0)}(\omega) = \frac{e^2}{h} \int dE \text{Tr}[A_{\alpha\gamma}^{(0)}(L, E, E + \hbar\omega) A_{\gamma\alpha}^{(0)}(L, E + \hbar\omega, E)] \times \{f_\alpha(E)[1 - f_\gamma(E + \hbar\omega)] + [1 - f_\alpha(E)]f_\gamma(E + \hbar\omega)\}. \quad (4)$$

Here $f_\alpha(E)$ is the Fermi function in lead α ; the notation $A_{\alpha\gamma}^{(0)}(L, E, E')$ indicates the $N_\alpha \times N_\gamma$ block of the matrix $A^{(0)}(L, E, E')$; $\text{Tr}[C_{\alpha\alpha}]$ is the trace of the square matrix $C_{\alpha\alpha}$ which implies summing over the N_α propagating channels of lead α . For energy-independent scattering, the integration over E can be straightforwardly performed and Eq. (4) reduces to the result found in [9], valid for a tunnel barrier or a quantum point contact. However, quite generally the current matrix A contains correlations at different energies separated by $\hbar\omega$ [10]. Here we consider the effect of these correlations on the finite-frequency noise of a chaotic quantum cavity, which can be treated in the framework of random matrix theory (RMT). Specifically, we make use of [11] to obtain the ensemble averaged, energy-dependent quantity $\langle \text{Tr}[A_{\alpha\gamma}^{(0)}(L, E, E + \hbar\omega) A_{\gamma\alpha}^{(0)}(L, E + \hbar\omega, E)] \rangle$ (no sum over α and γ). In view of Eq. (2), this amounts to the calculation of the average trace of the product of two scattering matrices, which we achieve with the help of [11], $\langle \text{Tr}[s_{\alpha\gamma}^\dagger(E_1) s_{\alpha\gamma}(E_2)] \rangle \equiv (N_\alpha N_\gamma / N) g(E_2 - E_1)$, where $g(E) = [1 - iE\tau_D/\hbar]^{-1}$. Similarly, we need

$$\langle \text{Tr}[s_{\gamma\alpha}^\dagger(E_1) s_{\gamma\delta}(E_2) s_{\varepsilon\delta}^\dagger(E_3) s_{\varepsilon\alpha}(E_4)] \rangle = \frac{N_\alpha N_\gamma}{N^2} \left[\delta_{\alpha\delta} N_\varepsilon g(E_2 - E_1) g(E_4 - E_3) + \delta_{\gamma\varepsilon} N_\delta g(E_4 - E_1) g(E_2 - E_3) - \frac{N_\delta N_\varepsilon}{N} \frac{g(E_2 - E_1) g(E_4 - E_3) g(E_4 - E_1) g(E_2 - E_3)}{g(E_2 + E_4 - E_1 - E_3)} \right].$$

These results depend on the cavity's dwell-time τ_D as well as on the number of channels $N_{L,R}$ in the leads. Certain inequalities apply to these quantities. First of all, we assume τ_D to be much longer than the Ehrenfest time that characterizes the spreading of a wave packet in the cavity [12]. This ensures that the electrons spend enough time in the cavity

for quantum chaos to fully develop and RMT to apply. Hence our results are universal in the sense that they do not depend on details of the cavity. Second, the results of [11] were obtained for a large scattering matrix, i.e., in the limit $N \gg 1$. We ignore corrections of relative order $\mathcal{O}(1/N)$, i.e., weak localization is not taken into account. Finally, we also ignore renormalization of transport by interactions [13], assuming that both leads are well-connected to the cavity with $N_L, N_R \gg 1$. However, the openings to the leads are much smaller than the total circumference of the cavity in order for universality to hold.

Performing the ensemble-average of (4), we find the frequency-dependent noise of a non-interacting chaotic cavity at finite temperature T and applied bias V ,

$$S_{LL}^{(0)}(\omega) = \frac{e^2}{h} \frac{1}{1 + \omega^2 \tau_D^2} \left\{ \frac{2\hbar\omega}{1 - e^{-\beta\hbar\omega}} \left[\frac{N_L N_R}{N} \left(1 - \frac{N_L N_R}{N^2} \right) + \omega^2 \tau_D^2 \frac{N_L}{2} \left(1 + \frac{N_L^2}{N^2} + \frac{N_R^2}{N^2} \right) \right] + \left[\frac{\hbar\omega + eV}{1 - e^{-\beta(\hbar\omega + eV)}} + \frac{\hbar\omega - eV}{1 - e^{-\beta(\hbar\omega - eV)}} \right] \left[\frac{N_L^2 N_R^2}{N^3} + \omega^2 \tau_D^2 \frac{N_L^2 N_R}{N^2} \right] \right\}, \quad (5)$$

where $\beta = 1/k_B T$. In the limit $\omega \rightarrow 0$, Eq. (5) reduces to the known result for zero-frequency noise of a chaotic cavity [14] which has been studied experimentally [15]. We will discuss the frequency-dependent spectral function below, after interaction effects have been included.

In order to treat the case of an interacting chaotic cavity we follow the general framework of Ref. [16]. The central idea is that fluctuations of particle current, as given by Eq. (1), lead to a pile-up of charge in the cavity that is subsequently compensated by displacement currents induced at the contacts and the gate. The total current at a given contact can be written as the sum of particle current and displacement current at that contact. To determine the displacement current, the uniform self-consistent potential of the cavity must be found [17], a problem that can be solved explicitly [16, 18]. It turns out that the resulting total current operator for the left lead is still given by Eq. (3), however the current matrix $A^{(0)}$ should be replaced by an effective current matrix $A = A^{(0)} + \Delta A$, where the correction ΔA includes the displacement contribution. This approach guarantees current conservation at finite frequency: the sum of all currents at the contacts of the sample together with the displacement current at the gate is zero. The explicit form of the correction ΔA reads [16]

$$\Delta A_{\gamma\delta}(\alpha, E, E + \hbar\omega) = i2\pi\hbar\omega \mathcal{G}_\alpha(\omega) \mathcal{N}_{\gamma\delta}(E, E + \hbar\omega), \quad (6)$$

where

$$\mathcal{N}_{\gamma\delta}(E, E') = \frac{i}{2\pi} \frac{s_{\alpha\gamma}^\dagger(E) [s_{\alpha\delta}(E) - s_{\alpha\delta}(E')]}{E' - E} \quad (7)$$

is the density of states matrix and $\mathcal{G}_\alpha(\omega)$ a frequency dependent response function, proportional to the emittance [19] of the cavity. In the linear response regime,

$$\mathcal{G}_\alpha(\omega) = \frac{N_\alpha}{N} \frac{e^2 N_F}{C + e^2 N_F} \frac{1}{1 - i\omega\tau}, \quad (8)$$

where the frequency-dependence is governed by the charge relaxation time τ .

Turning to the noise, we replace $A^{(0)}$ by A in Eq. (4) and find the additional contributions to noise related to the interaction correction ΔA . Performing the ensemble averaging of these terms ($\langle A^{(0)} \Delta A \rangle$, $\langle \Delta A A^{(0)} \rangle$ and $\langle \Delta A \Delta A \rangle$), we obtain the full noise spectral function: *it is given by Eq. (5), upon replacing the dwell time τ_D by the charge relaxation time τ* . This is our central result, which we will discuss in several relevant limits.




FIG. 2: (a) Frequency-dependent symmetrized noise $S_{\text{symm}}(\omega)$ in units G/β of an interacting chaotic cavity ($N_L/N = 0.5$) with a few values of charge relaxation time: from top $\tau/(\hbar\beta) = 10, 3, 1, 0.3, 0.1$; the bottom one corresponds to energy-independent scattering $\tau = 0$. Inset: corresponding circuit model. (b) Frequency-dependent unsymmetrized quantum noise; parameters as in (a).

If $V \rightarrow 0$, we find the non-symmetrized, equilibrium noise spectrum,

$$S_{LL}(\omega) = \frac{e^2}{h} \frac{N_L N_R}{N} \frac{2\hbar\omega}{1 - e^{-\beta\hbar\omega}} \frac{1 + \omega^2\tau^2 N/N_R}{1 + \omega^2\tau^2}. \quad (9)$$

The symmetrized spectrum $[S_{LL}(\omega) + S_{LL}(-\omega)]/2$ is plotted in Fig. 2a. According to the fluctuation dissipation theorem, this is connected to the real part of the AC conductance of the interacting cavity. We find

$$\Re[G_{LL}(\omega)] = \frac{e^2}{h} \frac{N_L N_R}{N} \frac{1 + \omega^2\tau^2 N/N_R}{1 + \omega^2\tau^2},$$

in agreement with a direct calculation [20]. At equilibrium, the cavity corresponds to the effective circuit depicted in the inset of Fig. 2a. Here, G_L and G_R are the quantum conductances of the left and right lead respectively, whereas C_μ is the series capacitance of the true geometric capacitance C and the quantum capacitance $e^2 N_F$ of the cavity. At low frequencies, the effect of this capacitance can be ignored, and the noise is that of the series conductance $G = G_L G_R / (G_L + G_R) = (N_L N_R / N) e^2 / h$. At high frequency, C_μ opens a new current path thereby increasing the AC conductance and hence the noise. The corresponding frequency scale is set by τ^{-1} , which is the inverse RC time of the two resistances G_L^{-1} and G_R^{-1} in parallel, in combination with the capacitance C_μ . Quite generally, the non-interacting case corresponds to the limit of large geometric capacitance, such that the quantum capacitance – and hence the dwell time τ_D – determines the dynamics. In this limit the noise spectra are obtained from Eq. (5). The result (9) for non-symmetrized noise is




FIG. 3: (a) Frequency dependence of the Fano factor at a few values of N_L/N . (b) The second cumulant for a cavity with $N_L/N = 0.9, 0.75, 0.5$, and 0.3 from top to bottom.

plotted in Fig. 2b. There is a pronounced difference between noise at negative and positive frequencies, corresponding respectively to absorption and emission. For negative frequencies a peculiarity develops at $\omega \sim -\tau^{-1}$ as a manifestation of enhanced absorption due to charged fluctuations.

As to the non-equilibrium noise for $eV \gg k_B T, \hbar\omega$ we have

$$S_{LL}(\omega) = \frac{N_L N_R}{N^2} e \langle I \rangle \frac{1 + \omega^2 \tau^2 N/N_R}{1 + \omega^2 \tau^2}, \quad (10)$$

where we defined the average current through the cavity $\langle I \rangle = GV$. The Fano factor $F(\omega) \equiv S_{LL}(\omega)/(e \langle I \rangle)$ is plotted in Fig. 3a. At zero frequency this gives the result $S_{LL}(0) = F(0)e \langle I \rangle$, which is characterized by the shot-noise reduction factor $F(0) = N_L N_R / N^2$, in agreement with [14]. At frequencies exceeding $1/\tau$, the Fano factor tends to the value N_L/N , corresponding to an increase of the noise by N/N_R .

We finally consider the time-dependent second cumulant of charge transport [21] for the left lead, given by

$$\langle\langle q^2 \rangle\rangle(t) = 2 \int \frac{d\omega}{2\pi} S_{LL}(\omega) \frac{1 - \cos(\omega t)}{\omega^2}. \quad (11)$$

Inserting (10) into (11) we have

$$\langle\langle q^2 \rangle\rangle(t) = \frac{N_L N_R}{N^2} e \langle I \rangle t \left[1 + \frac{N_L}{N_R} \frac{\tau}{t} (1 - e^{-t/\tau}) \right]. \quad (12)$$

The time dependence of $\langle\langle q^2 \rangle\rangle / (F_0 e \langle I \rangle \tau)$ is plotted in Fig. 3b again at a few values of N_L/N . We see that the universal long time limit is reached only after a transient time τ ; the ratio of the slopes at early and late times is determined by the asymmetry and given by N/N_R .

Finally, we comment on the experimental feasibility of a measurement of the above found noise spectra. For the cavity studied in the experiment [15], the various conditions for our calculations to be valid appear to be met. The dwell time τ_D is in the ns range; the large area, $> 10 (\mu\text{m})^2$ for a typical cavity, allows for capacitances exceeding 10 fF. We thus estimate $\tau_C \sim 20$ ps, thereby giving a charge relaxation time τ of the same order. The condition $\omega\tau \sim 1$ can then be reached, using a Josephson junction in the quantum limit as a detector, where the level spacing (plasma frequency) is $\sim 10\text{--}100$ GHz. Our results may be helpful for future experiments on other mesoscopic conductors also, such as a diffusive metallic wire capacitively coupled to a nearby ground plane [22].

We thank T. Heikkilä, F. Pistolesi, R. Whitney and especially P. Brouwer, M. Büttiker and D. Prober for useful discussions and comments. Financial support from Academy of Finland and from Institut Universitaire de France is gratefully acknowledged.

-
- [1] Ya.M. Blanter and M. Büttiker, Phys. Rep. **336**, 1 (2000).
 - [2] *Quantum Noise in Mesoscopic Physics*, edited by Yu. V. Nazarov (Kluwer, Dordrecht, 2003).
 - [3] G. Johansson, A. Käck, and G. Wendin, Phys. Rev. Lett. **88**, 046802 (2002); A. Käck, G. Wendin, and G. Johansson, Phys. Rev. B **67**, 035301 (2003); A.V. Galaktionov, D.S. Golubev, and A.D. Zaikin, Phys. Rev. B **68**, 085317 (2003).
 - [4] B. Trauzettel, I. Safi, F. Dolcini, and H. Grabert, Phys. Rev. Lett. **92**, 226405 (2004); F. Dolcini, B. Trauzettel, I. Safi, and H. Grabert, Phys. Rev. B **71**, 165309 (2005); A.V. Lebedev, A. Crépieux, and Th. Martin, Phys. Rev. B **71**, 075416 (2005).
 - [5] R. Aguado and L.P. Kouwenhoven, Phys. Rev. Lett. **84**, 1986 (2000); R.J. Schoelkopf *et al.*, in Ref. [2]; R. Deblock, E. Onac, L. Gurevich, and L.P. Kouwenhoven, Science **301**, 203 (2003); O. Astafiev *et al.*, Phys. Rev. Lett. **93**, 267007 (2004); J.P. Pekola *et al.*, cond-mat/0502446; J. Claudon, A. Fay, L.P. Lévy, and O. Buisson (unpublished).
 - [6] B. Reulet, J. Senzier and D.E. Prober, Phys. Rev. Lett. **91**, 196601 (2003); Yu. Bomze *et al.*, cond-mat/0504382 (unpublished); A.V. Galaktionov, D.S. Golubev, and A.D. Zaikin, Phys. Rev. B **68**, 235333 (2003); K.E. Nagaev, S. Pilgram, and M. Büttiker, Phys. Rev. Lett. **92**, 176804 (2004).
 - [7] M. Büttiker, Phys. Rev. B **46**, 12485 (1992).
 - [8] We sum over repeated indices unless stated otherwise.
 - [9] V.A. Khlus, Zh. Eksp. Teor. Fiz. **93**, 2179 (1987) [Sov. Phys. JETP **66**, 1243 (1987)].
 - [10] B. Reulet and D.E. Prober, Phys. Rev. Lett. **95**, 066602 (2005).
 - [11] M.L. Polianski and P.W. Brouwer, J. Phys. A: Math. Gen. **36**, 3215 (2003).
 - [12] O. Agam, I. Aleiner, and A. Larkin, Phys. Rev. Lett. **85**, 3153 (2000).
 - [13] K. Flensberg, Phys. Rev. B **48**, 11156 (1993); K.A. Matveev, *ibid.* **51**, 1743 (1995); M. Kindermann and B. Trauzettel, Phys. Rev. Lett. **94**, 166803 (2005).
 - [14] R.A. Jalabert, J.-L. Pichard, and C.W.J. Beenakker, Europhys. Lett. **27**, 255 (1994); Ya.M. Blanter and E.V. Sukhorukov, Phys. Rev. Lett. **84**, 1280 (2000).
 - [15] S. Oberholzer *et al.*, Phys. Rev. Lett. **86**, 2114 (2001).
 - [16] M.H. Pedersen, S.A. van Langen, and M. Büttiker, Phys. Rev. B **57**, 1838 (1998).
 - [17] I.L. Kurland, I.L. Aleiner, and B.L. Altshuler, Phys. Rev. B **62**, 14886 (2000); P.W. Brouwer, A. Lamacraft, and K. Flensberg, *ibid.* **72**, 075316 (2005); Phys. Rev. Lett. **94**, 136801 (2005).
 - [18] M. Büttiker, A. Prêtre, and H. Thomas, Phys. Rev. Lett. **70**, 4114 (1993); A. Prêtre, H.

- Thomas, and M. Büttiker, Phys. Rev. B **54**, 8130 (1996).
- [19] M. Büttiker, J. Phys.: Condens. Matter **5**, 9361 (1993).
 - [20] P.W. Brouwer and M. Büttiker, Europhys. Lett. **37**, 441 (1997).
 - [21] L. S. Levitov, H. W. Lee, and G. B. Lesovik, J. Math. Phys. **37**, 4845 (1996).
 - [22] Here, a more elaborate treatment of screening may be needed as the uniform potential model breaks down [18].